

DATA SHEET

Communications - AC 900F Communication interfaces

Freelance hardware selector

The AC 900F controller family includes a selection of communications modules that make it possible to access a wide range of field devices and third-party systems. It has slots for assembling Communication Interface Module. The interfaces include:

- Ethernet-based interfaces/protocols
- Serial communications
- Interfaces to ABB equipment
- Communication interfaces to heritage systems









Specific feature ¹	CI 773F	CI 910F	CI 930F	CI 940F	
General info		·			
Article number	3BDH000395R0001	3BDH001005R0001	3BDH001010R0002	3BDH001015R0001	
Communication protocol	Communication Interface, PROFIBUS DP Master	Three CAN Bus channels. ABB CAN Bus protocol. D-Sub terminals (9-pole). Software version 2016 or higher is mandatory. White housing. Requires one coupler bus slot on the CPU module.	Communication Interface, PROFIBUS DP Master	FF-HSE Communication Module	
Life cycle status	Active				
Transmission speed	9.6 kBit/s to 12 MBit/s	max. 1 MBit/s	9.6 kBit/s to 12 MBit/s	10/100 Mbit/s (full and half duplex), Auto-Negotiation and Auto MDI-X	
Line redundancy	No		Yes		
Hot Swap	Yes				
Dimensions					
Width	28 mm				
Height	135 mm	152 mm			
Depth	75 mm		85 mm	75 mm	
Weight	96 g	178 g	115 g	145 g	
Environment and certific	ation				
RoHS compliance	Directive 2011/65/EU, (EU) 2	Directive 2011/65/EU, (EU) 2015/863			
WEEE compliance	Directive 2012/19/EU	Directive 2012/19/EU			

¹ For detailed information on each module, please visit: freelancehardwareselector.automation.abb.com



solutions.abb/freelance solutions.abb/controlsystems

We reserve the right to make technical changes to the products or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not assume any responsibility for any errors or incomplete information in this document.

We reserve all rights to this document and the items and images it contains. The reproduction, disclosure to third parties or the use of the content of this document – including parts thereof – are prohibited without ABB's prior written permission.

Copyright© 2024 ABB All rights reserved